A PROTECT YOUR FOCUS

IN PUBLIC SAFETY, FOCUS IS YOUR GREATEST RESOURCE. MAKE SURE IT'S PROTECTED WITH APX NEXT[®].

A MASSIVE ADVANCE IN MISSION-CRITICAL VOICE AND DATA

Your radio is your lifeline. APX NEXT is our next step in advancing it. It's designed to military standards for extreme ruggedness. The touchscreen works with or without gloves—in rain, dirt, and dust. Digital mics and high-power speakers deliver our best audio ever, while SmartConnect keeps you connected even beyond your P25 system. The result is a radio that works when you need it, without pause, distraction or doubt.

EFFORTLESS IS ALWAYS IN REACH

* 11:30

Ξ

5

=

All Messages

My Status

En Route

<u>11 8 7 1 1 1 </u>

East Zone

Patrol 1

Clark, Robert

F

New Conversation

On my way

4

APX NEXT is designed for effortless usability when everything is on the line. Intuitive knobs and buttons are easily distinguished by touch. A mission-critical touchscreen makes it fast and easy to operate your radio. ViQi understands a huge range of natural language voice commands, so you can operate the radio with eyes-up awareness. Every interaction is simple, fast and logical. You stay focused on what matters—your mission and your safety.

BRING NEW INTELLIGENCE TO THE POINT OF ENGAGEMENT

APX NEXT mission-critical apps bring new intelligence to the field. ViQi enables natural language database queries, rapidly giving vital information, and letting dispatchers stay focused on critical situations. And as part of our unique, end-to-end public safety ecosystem, APX NEXT data and operations are secure, and new capabilities can be seamlessly added as your needs evolve.

UPDATE YOUR FLEET IN MINUTES, NOT MONTHS

APX NEXT gives you back time: a cloud-based provisioning system prepares radios before they arrive. Remote updating keeps radios in the field, with zero touch and zero downtime. MyView Portal provides direct access to subscriptions, warranties and licenses, and a range of services helps you manage your operation. With APX NEXT, your ownership experience is streamlined, so your valuable resources stay focused and ready.



MISSION-CRITICAL DESIGN



FEATURES

OPERATION MODES

| Digital Trunking: 9600 Baud APCO P25 Phase 1 FDMA and Phase 2 TDMA |
|---|
| Digital Conventional: APCO 25 |
| Analog Trunking: 3600 Baud SmartNet®, SmartZone®, Omnilink® |
| Analog Conventional: MDC 1200 |
| ASTRO® 25 Integrated Voice and Data |
| SmartConnect Multi-net Connectivity* |
| |

FREQUENCY BANDS

| All-band: Simultaneous Operation in VHF, UHF Range 1, |
|--|
| UHF Range 2, 700 and 800 MHz Bands |
| Available in Multi-band and Single-band Configurations |
| Up to 3000 Channels |
| Up to 125 Zones |

ADDITIONAL CONNECTIVITY

| Bluetooth (Version 5.0) |
|---|
| WiFi (802.11a/b/g/n/ac), 2.4 and 5 GHz Bands |
| LTE (FirstNet®, Verizon, & Bell Mobility - certified) |
| NFC (Near-Field Communications)** |

AUDIO FEATURES

| 3 W Speaker with Adaptive Equalization |
|---|
| 2 Internal Digital Microphones |
| Adaptive Dual-sided Operation |
| Adaptive Noise Suppression Intensity |
| Adaptive Gain Control |
| Adaptive Windporting |
| IMPRES [™] Audio Accessory Compatibility |

MANAGEMENT

| Customer Programming Software (CPS) |
|-------------------------------------|
| RadioCentral [™] * |
| SmartProgramming* |
| Radio Management* |

LOCATION-TRACKING

| Built-in GNSS (GPS, Galileo, GLONASS) and A-GPS |
|---|
| SmartLocate and Indoor Positioning* |
| Mission-critical Geofence** |
| SmartMapping* |

SECURITY

| 256-bit AES* |
|--|
| Single-key ADP Encryption* |
| Software Key |
| P25 Authentication* |
| Multikey for 128 Keys and Multi-algorithm* |
| Over-The-Air Key Loading*** |
| Over-The-Air Rekeying (OTAR)* |

INGRESS PROTECTION

| IP6x Dust |
|------------------------------------|
| IPx8 Submersion (2 m, 4 hr) |
| MIL-STD Delta-T, 512.X Procedure 1 |

MESSAGING

| Text Messaging |
|-----------------------------|
| Freeform or Canned Messages |
| SmartMessaging* |

USER INTERFACE

| 3.6" Mission-critical Touchscreen: 800x480 TFT 24-bit Full Color Transflective Display, 1 mm Toughened Glass Lens |
|--|
| O |
| Capacitive Touch Technology: Usable with Gloves Up to 4 mm Thick, Resistant to False Actuation from Fresh or Salt Water, Snow, Ice, Dirt or Grease |
| High Velocity User Interface: Large Touch Targets, Shallow Menu Hierarchy, Home Screen Information at a Glance, Integrated Applications |
| 1.2" Top Display: 200x112 TFT 18-bit Color Transflective Screen, 1 Line of Icons, 2 Lines of Text, 14 Characters per Line, 2 mm Toughened Glass Lens |
| PTT Button: 1.32 x 0.54 in (33.5 x 13.8 mm) |
| 16-position Channel Selector |
| Angled Power/Volume Knob |
| Large Orange Emergency Button |
| 3 Programmable Side Buttons (1-dot, 2-dot, purple) |
| Concentric 2-position Switch |
| ABC Zone Switch |
| ViQi Button (3-dot) |
| Display On/Off/Home Button |

ViQi VOICE INTERACTION

| Customizable Voice Announcements |
|---|
| Voice Control: Radio operation with intuitive commands* |
| Virtual Partner Service* |

ENERGY

| Standard 4400 mAh Battery | |
|--|---|
| Optional High Capacity 5650 mAh Battery* | • |
| IMPRES 2 Smart Battery Technology | |

SENSORS

| Ambient Light |
|--|
| Accelerometer x2 (Display Orientation, Man Down) |
| Magnetometer (eCompass) |

OTHER FEATURES

| Radio Profiles | |
|-------------------------|--|
| Enhanced Data* | |
| Multicast Voting Scan* | |
| Man Down / Fall Alert* | |
| DVRS PSU* | |
| Digital Tone Signaling* | |

DIMENSIONS

| Radio with Standard Battery, no Antenna | |
|--|--|
| Height: 5.4 in (138 mm) | |
| Width: 2.5 in (63 mm) | |
| Depth: 1.7 in (43 mm) | |
| Weight: 18.5 oz (525 g) | |
| Radio with High Capacity Battery, no Antenna | |
| Height: 7.1 in (180 mm) | |
| Width: 2.5 in (63 mm) | |
| Depth: 1.7 in (43 mm) | |
| Weight: 22.8 oz (647 g) | |
| | |





1.7 in (43 mm)



PERFORMANCE

TRANSMITTER

| | Footnote | VHF | UHF Range 1 | UHF Range 2 | 700 MHz | 800 MHz |
|---|----------|-----------------------|-----------------------|-----------------------|-----------------------|-------------------------|
| Frequency Range / Bandsplits | - | 136-174 MHz | 380-470 MHz | 450-520 MHz | 762-776, 792-806 MHz | 806-825, 851-870 MHz |
| Channel Spacing | 1 | 12.5 / 20 / 25 kHz |
| Maximum Frequency Separation | - | Full Bandsplit |
| Rated RF Output Power (Adjustable) | 2 | 1-6 W | 1-5 W | 1-5 W | 1-2.5 W | 1-3 W |
| Frequency Stability (-30 °C to +60 °C; +25 °C Ref.) | 2 | ±1.0 ppm |
| Modulation Limiting (12.5 / 20 / 25 kHz Channel) | 2 | ±2.5 / ±4 / ±5 kHz |
| Emissions (Conducted and Radiated) | 2 | -75 dBc |
| Audio Response | 2 | +1, -3 dB |
| FM Hum and Noise (12.5 / 25 kHz Channel) | 2 | -53 / -55 dB | -52 / -54 dB | -51 / -54 dB | -50 / -55 dB | -49 / -53 dB |
| Audio Distortion (12.5 / 25 kHz Channel) | 2 | 0.75% / 0.75% | 0.75% / 0.75% | 0.75% / 0.75% | 0.85% / 0.85% | 0.85% / 0.85% |
| RECEIVER | | | | | | |
| | Footnote | VHF | UHF Range 1 | UHF Range 2 | 700 MHz | 800 MHz |
| Frequency Range / Bandsplits | - | 136-174 MHz | 380-470 MHz | 450-520 MHz | 762-776, 799-806 MHz | 851-870 MHz |
| Channel Spacing | 1 | 12.5 / 20 / 25 kHz |
| Maximum Frequency Separation | - | Full Bandsplit |
| Frequency Stability (-30 °C to +60 °C; +25 °C Ref.) | 2 | ±1.0 ppm |
| Analog Sensitivity (12 dB SINAD) | 2 | 0.178 µV (-122.0 dBm) | 0.211 µV (-120.5 dBm) | 0.211 µV (-120.5 dBm) | 0.224 µV (-120.0 dBm) | 0.237 µV (-119.5 dBm |
| Digital Sensitivity (1% BER) | 3 | 0.266 µV (-118.5 dBm) | 0.298 µV (-117.5 dBm) | 0.298 uV (-117.5 dBm) | 0.335 µV (-116.5 dBm) | 0.335 µV (-116.5 dBm |
| Digital Sensitivity (5% BER) | 3 | 0.158 µV (-123.0 dBm) | 0.178 µV (-122.0 dBm) | 0.178 µV (-122.0 dBm) | 0.224 µV (-120.0 dBm) | 0.224 µV (-120.0 dBm |
| Selectivity (12.5 / 25 kHz Channel) | 2 | 77 / 84 dB | 74 / 81 dB | 74 / 81 dB | 72 / 80 dB | 72 / 79 dB |
| Intermodulation Rejection | 2 | 82 dB | 80 dB | 80 dB | 80 dB | 80 dB |
| Spurious Rejection | 2 | 98 dB | 95 dB | 95 dB | 98 dB | 98 dB |
| FM Hum and Noise (12.5 / 25 kHz Channel) | 2 | 55 / 59 dB | 54 / 58 dB | 54 / 58 dB | 53 / 57 dB | 52 / 56 dB |
| Audio Distortion | 2 | 0.90% | 0.90% | 0.90% | 0.90% | 0.90% |
| | | | | | | |



IMPRES[™]2 BATTERIES

| IMPRES Z BATTERI | | | | | | |
|-------------------------------------|-------------------|---|---|-------------------------|--|--|
| | Footnote | Part No | Capacity | Availability | | |
| Standard | - | NNTN9216 | 4400 mAh | Included | | |
| High Capacity | - | NNTN9089 | 5650 mAh | Optional | | |
| Standard HazLoc | 4 | NNTN9217 | 4400 mAh | Optional | | |
| High Capacity HazLoc | 4 | NNTN9090 | 5650 mAh | Optional | | |
| ENCRYPTION | | | | | | |
| Supported Encryption Algorith | | 256-bit AES, DES alized Algorithm | S, DES-XL, DES- | OFB, DVP-XL, | | |
| Encryption Algorithm Capacity | 8 | | | | | |
| Encryption Keys per Radio | | 1024 Keys, Programmable for 128 Common Key References (CKR) or 16 Physical Identifiers (PID) | | | | |
| Encryption Keying | | Local Key Loader and Over-the-Air Rekeying (OTAR) | | | | |
| Synchronization | | XL - Counter Addressing OFB - Output Feedback | | | | |
| Vector Generator | | NIST-Approved Random Number Generator | | | | |
| Encryption Type | Digi | Digital and SecureNet, TLS1.2, SRTP | | | | |
| Key Storage | | Tamper-protected Volatile or Non-volatile Memory | | | | |
| Key Erasure | Key | board Command a | nd Tamper Dete | ection | | |
| Standards | FIPS | FIPS 140-3 Level 1 and Level 3, FIPS 197 | | | | |
| Device Certificates | x.50 | x.509v3 ECC-P384, x.509v3 RSA-2048 | | | | |
| Cipher Suites FIPS 140-2 Level 1 | TLS TLS TLS | HE_ECDSA_WITH _ECDHE_RSA_W _ECDHE_RSA_W _RSA_WITH_AES P_AEAD_AES_25 | ITH_AES_256_ ITH_AES_256_ S_256_GCM_S | _GCM_SHA384 _CBC_SHA | | |
| | | | | | | |

COLOR

| Standard Color | | Black/Gray | |
|---|-------------------------|-----------------|------------------------|
| Optional Side Panel Colors (Supplied as F | | Retro-fit Kits) | |
| HN001451A02 | GCAI Side, Red | HN001452A02 | PTT Side, Red |
| HN001451A03 | GCAI Side, Blue | HN001452A03 | PTT Side, Blue |
| HN001451A04 | GCAI Side, Coyote Brown | HN001452A04 | PTT Side, Coyote Brown |
| HN001451A05 | GCAI Side, Yellow | HN001452A05 | PTT Side, Yellow |
| HN001451A06 | GCAI Side, Orange | HN001452A06 | PTT Side, Orange |
| HN001451A07 | GCAI Side, Impact Green | HN001452A07 | PTT Side, Impact Green |
| | | | |

| WINLELSS | | |
|---------------------------------|----------|---|
| LTE | Footnote | |
| Bands Supported | - | 2, 4, 12, 13, 14, 17 |
| Bands (Hardware Ready) | - | 5 |
| Device Category | - | 4 |
| Certifications | 5 | FirstNet®, Verizon, Bell Mobility |
| WiFi | | |
| Standards Supported | | 802.11a/b/g/n/ac |
| Frequency Range | | 2400-2472, 5180-5825 MHz |
| Security | | Supports WPA-2, WPA, WEP |
| Capacity | | Up to 20 SSIDs |
| Bluetooth | | |
| Version | | 5.0 |
| Frequency Range | | 2402 - 2480 MHz |
| Security | | 128-bit AES-CCM Encryption |
| AUDIO | | |
| Audio Output Power at Rated | | 3 W |
| Audio Output Power at Max | | 5 W |
| Audio Response (EIA) | | +1, -3 dB |
| Speech Loudness at 12 in (300 r | nm) | 105 Phon |
| Audio Features | | Adaptive Equalization Adaptive Dual-sided Operation Adaptive Noise Suppression Intensity Adaptive Gain Control Adaptive Windporting IMPRES Audio |

LOCATION-TRACKING

| | Footnote | |
|----------------------|----------|---|
| Constellations | - | GPS, Galileo, GLONASS, A-GPS |
| Tracking Sensitivity | - | -159 dBm |
| Accuracy | 6 | <5m (95%) |
| Cold Start | 6 | <60 Seconds (95%) |
| Hot Start | 6 | <5 Seconds (95%) |
| Mode | - | Autonomous (Assisted only with LTE service) |

ENVIRONMENTAL AND REGULATORY

MIL-STD 810

| | MIL-STD 810C | | MIL-STD 810D | | MIL-STD 810E | | MIL-STD 810F | | MIL-STD 810G/H | |
|-------------------|--------------|-----------------|--------------|-------------|--------------|-------------|--------------|---------------|----------------|---------------|
| | Method | Proc./Cat. | Method | Proc./Cat. | Method | Proc./Cat. | Method | Proc./Cat. | Method | Proc./Cat. |
| Low Pressure | 500.1 | | 500.2 | | 500.3 | 11 | 500.4 | II | 500.5 | |
| High Temperature | 501.1 | 1, 11 | 501.2 | I/A1, II/A1 | 501.3 | I/A1, II/A1 | 501.4 | I/Hot, II/Hot | 501.5 | I/A1, II/A1 |
| Low Temperature | 502.1 | | 502.2 | I/C3, II/C1 | 502.3 | I/C3, II/C1 | 502.4 | I/C3, II/C1 | 502.5 | I/C3, II/C1 |
| Temperature Shock | 503.1 | I | 503.2 | I/A1, C3 | 503.3 | I/A1, C3 | 503.4 | I | 503.5 | I/C |
| Solar Radiation | 505.1 | II | 505.2 | I | 505.3 | I | 505.4 | I | 505.5 | I/A1 |
| Rain | 506.1 | 1, 11 | 506.2 | 1, 11 | 506.3 | I, II | 506.4 | I, III | 506.5 | I, III |
| Humidity | 507.1 | II | 507.2 | | 507.3 | | 507.4 | 1 Proc | 507.5 | II/Aggravated |
| Salt Fog | 509.1 | | 509.2 | I | 509.3 | I | 509.4 | 1 Proc | 509.5 | 1 Proc |
| Blowing Dust | 510.1 | I | 510.2 | I | 510.3 | I | 510.4 | I | 510.5 | I |
| Blowing Sand | 1 Proc | 1 Proc | 510.2 | II | 510.3 | II | 510.4 | II | 510.5 | |
| Submersion | 512.1 | | 512.2 | I | 512.3 | I | 512.4 | I | 512.5 | I |
| Vibration | 514.2 | VIII/F, Curve-W | 514.3 | I/10, II/3 | 514.4 | I/10, II/3 | 514.5 | I/24 | 514.6 | I/24 |
| Shock | 516.2 | I, III, V | 516.3 | I, V, VI | 516.4 | I, V, VI | 516.5 | I, V, VI | 516.6 | I, V, VI |
| Shock (Drop) | 516.2 | 11 | 516.3 | IV | 516.4 | IV | 516.5 | IV | 516.6 | IV |

ENVIRONMENTAL

| | Footnote | |
|----------------------------------|----------|--|
| Operating Temperature | 7 | -30 to +60 °C (-22 to +140 °F) |
| Storage Temperature | 7 | -40 to +85 °C (-40 to +185 °F) |
| Humidity | - | Per MIL-STD 810 |
| ESD | - | IEC 61000-4-2 |
| Dust Resistance | - | IP6X |
| Water Resistance (Submersion) | - | IPX8 (2 meters, 4 hours) MIL-STD Delta-T, 512.X Procedure 1 |

FOOTNOTES:

- Province 18:
 Please refer to local regulations for available channel bandwidths.
 Measured conductively in analog mode per TIA / EIA 603 under nominal conditions, and at 1 W Rated Audio for Rx. Selectivity measured using the TIA-603 single-tone method.
 Measured conductively in digital mode per TIA / EIA IS 102.
 Listed by UL to non-incendive standards: UL 121201 and CAN/CSA C22.2 No. 213-17 as safe for use in Class I, Division 2, Groups A, B, C, D; Class II, Division 2, Groups F, G; Class III Hazardous Locations.
- SIM cards for the listed carriers can be pre-installed at the Motorola Solutions factory or supplied by the end user via Bring Your Own SIM (BYOS) for certified carriers.

REGULATORY

| FCC ID | AZ489FT7119 |
|-----------------------|--|
| IC ID | 109U-89FT7119 |
| LMR | 8K10F1D, 8K10F1E, 8K10F1W, 11K0F3E, 16K0F3E, 20K0F1E |
| Bluetooth | 1M18G1D, 1M1F1D, 2M1F1D |
| WiFi | 12M9G1D, 16M7D1D, 17M9D1D, 36M2D1D, 17M5D1D, 18M4D1D, 36M8D1D, 76M1D1D |
| LTE | Band 2 (1850.7 - 1900 MHz), Modulation: *G7D, *D7W Band 4 (1710.7 - 1745 MHz), Modulation: *G7D, *D7W Band 12 (699.7 - 711 MHz), Modulation: *G7D, *D7W Band 14 (788 - 798 MHz), Modulation *G7D, *D7W Band 17 (704 - 716 MHz), Modulation: *G7D, *D7W |
| All-band Model Number | H55TGT9PW8AN |
| | |

6. Measured conductively with >6 satellites visible at a nominal -130 dBm signal strength. Specs provided are 95th percentile values.

7. LMR only. Front display, LTE, WiFi, Bluetooth and GPS not available when radio internal temperature is below -20 °C (-4 °F). Hi-capacity battery required for operation between -20 °C (-4 °F) and -30 °C (-22 °F). Batteries should be charged at 0 to +45 °C (+32 to +113 °F) and stored at +20 to +25 °C (+68 to +77 °F). Reference motorolasolutions.com/batterycare

All specifications are subject to change without notice. For full details consult product service manual, document no. MN005643A01.





ACCESSORIES

EXPAND AND CUSTOMIZE YOUR RADIO'S FUNCTIONALITY WITH BEST-IN-CLASS ACCESSORIES.

AUDIO

HEAR AND BE HEARD LIKE NEVER BEFORE



XVP Remote Speaker Microphone

PMMN4135

- Loudest, clearest speaker New adaptive noise
- Four digital microphones suppression
- Enhanced windporting Dedicated ViQi button

ANTENNAS

DESIGNED FOR WEARABILITY



Whip All-band Antenna 200 mm (V,U,7/800 MHz) AN000297A01

Colored antenna ID bands are available for easy customization and come in packs of 10.

32012144001 Gray
 32012144002 Yellow
 32012144003 Green

32012144004 Blue 32012144005 Purple

CARRY

SECURE, EASY ACCESS





Hybrid Leather Carry Case PMLN7948 Standard Capacity PMLN7964 High Capacity **ENERGY** MAXIMIZED POWER,

LIFE AND MANAGEMENT



IMPRES 2 Multi-Unit Charger NNTN9115



IMPRES 2 Single-Unit Charger NNTN9199



IMPRES 2 Standard Capacity Battery NNTN9126 4400 mAh NNTN9127 4400 mAh UL Div 2 (see footnote 4)



IMPRES 2 High Capacity Battery NNTN9089 5650 mAh NNTN9090 5650 mAh UL Div 2 (see footnote 4)

For a complete list of accessories, please visit motorolasolutions.com/apxnext

MANAGED AND SUPPORT SERVICES

ACHIEVE MISSION CRITICAL PERFORMANCE

Rely on us to help you achieve your performance targets with the right service level you need for systems, devices and applications. Each package provides a higher level of support, transferring the risk and responsibility to Motorola Solutions.

Motorola Solutions provides a range of service capabilities, including:

MYVIEW

A web-based platform that gives you a transparent, single source view of fleet status and service delivery information to help make smarter, faster and more proactive decisions.

TECHNICAL SUPPORT

Industry certified technical engineers can troubleshoot and provide prompt resolution to any technical issues, whether on-site dispatch or remote.

HARDWARE REPAIR AND SOFTWARE MAINTENANCE

Ensure continuous security, performance and enhanced functionality of your two-way radios by getting access to APX NEXT certified and tested release software updates and upgrades and protect your radios from normal wear and tear.

ACCIDENTAL DAMAGE

Radios are protected from accidental breakage or liquid spills and physical damage. With state-ofthe-art diagnostic equipment all of your agency's radio components are protected in the event of an unexpected failure and are back in operation as soon as possible.

DEVICE PROGRAMMING

APX NEXT includes Customer Programming Software (CPS) for one-at-a-time programming. We can enable batch programming for radios with centralized management to dramatically reduce the time and resources needed to provision and update your radio fleet.

As an add-on service, our technical teams can help you provision and program your fleet of radios on-site and train your staff on the radio fleet commissioning and management.

PREVENTIVE MAINTENANCE

Our certified technicians conduct annual maintenance checks to help extend the useful life of your radios, reducing repair and replacement costs.



PROTECT YOUR FOCUS WHEN IT MATTERS MOST

For more information, please visit **motorolasolutions.com/apxnext**



Motorola Solutions, Inc. 500 West Monroe Street, Chicago, IL 60661 U.S.A. 800-367-2346 motorolasolutions.com MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylized M Logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners. © 2023 Motorola Solutions, Inc. All rights reserved. 11-2023 [JP05]

