## **IMPORTANT:**

- Before enrolling any sensors ensure that the Gateway and any Alarm Nodes have been set up and configured first.
- When installing LIVE OnePOD sensors, be sure to enroll the sensors (as shown below) before connecting the sensor to the stand. This is critical for allowing the sensor to enroll in the web server properly.

## **Enrollment Steps**



With the InVue LIVE Display app open on the device, select the "Add or Scan InVue Device Button.





Use the mobile device's camera to scan the code on the sensor, then select "Next".







Select the position where the merchandise will be displayed, then click "Next".

< LIVE	
Security Sensor Settings	
Where is this item located? Select a location, below	
Q SEARCH	
Locations	
QA ENV.   ALARM NODE #2	
A ENV.1   VERTICAL SENSOR #TEST1	1
1A ENV.6   TESTOVERNIGHT	
1A ENV.8   TESTOVERNIGHT-J IN PLAN	
1A ENV.7   TESTOVERNIGHT-I IN PLAN	
A ENV.1   VERTICAL SENSOR #16DB	1
A ENV.1   VERTICAL SENSOR #1635	
No assigned location. Not in plan.	
CANCEL	-

Scan or manually enter the UPC number, SKU number or Model number for the merchandise that will be on display in this position. This SKU, UPC or Model number should match the merchandise information on the site plan. Press the check mark when complete







Select the Alarm Node that the sensor will be paired with and select "Next".

**Note:** If an Alarm Node is offline it will not be selectable. Fixing the Alarm Node and getting it back online will allow it to be selected.

< LIVE	
Security Sensor Settings	
Assign to an Alarm Module	
Select one alarm from list, below	
Q SEARCH	
Alarm Modules	
ALARM NODE	-
ALARM NODE2	
WIRELESS EXPERIENCE SHOWCASE	

Verify all information is correct before hitting save. If any information needs to be edited, select the pencil icon to make any necessary changes. Once verified, click "Save".

2:10 🗘 😁 🕅 📥	•	<u></u>	U	ш
< LIVE				
	Settings			
Туре:	OnePOD Secu	urity Sens	sor	
Device ID:	00040010EE			
Merchandise:				
Samsung - Sam	sung Galaxy		1	
Section:				
Mobile Table			1	
Position:				
Position 10			1	
Alarm Module Nan	ne:			
Alarm Node			1	
				1
Cancel		Save		







8 It may take a few moments for the sensor to go through all of the necessary steps in the software. When the process is complete, the shield icon will turn green.

	A •	≅ •0• ÷▼ <b>▲</b>		€ ••• •
C LOCK ALL	DISPLAY SE	CURITY	C DISPLA	AY SECURITY
SECURE STAT	FUS (12)	ISSUES (1)	SECURE STATUS (12)	ISSUES (1)
Samsung, Mobile Tab	Samsung Galaxy	y >	Samsung, Samsung Mobile Table, Positio	Galaxy >
STATUS	INS	TALL PENDING	STATUS	(a)



The user must confirm that the merchandise on display matches the assigned merchandise. This process also tells the sensor to save the serial number for the stand that it is installed. This is an important step to ensure the accuracy and integrity of the planogram data. The "compliance issue" message is a reminder to complete this step. Ensure the sensor is seated on the correct stand and then press Confirm.

1 🗠 🐵 🕅 📥 🔹	® @ †♥ <b> </b>	2:1	13 D 💮 M 📥 🔸	
General				
erchandise:	Samsung - Samsung Galaxy		C Securi Lock S	ity Status: ARMED Status: UNLOCKED
ction:	Mobile Table			
ition:	Position 10		General	
gned To m:	Alarm Node		Merchandise:	Samsung - Samsung Galaxy
sues:	Compliance Issue		Section:	Mobile Table
t undate:	Fri Jun 03 2022 at		Position:	Position 10
si upuate.	02:11:10 PM		Assigned To	Alarm Node
teway:	LI7000-7268 Unit 2 in		Aldini.	
	RSSI : -73 dBm		Issues:	None
	SNR : 14.3 dB		Last update:	Fri, Jun 03, 2022 at 02:11:10 PM
Confirm that me ocation matche Otherwise,modif settings.	rchandise and confirm s info above. fy device		Gateway:	LI7000-7268 Unit 2 i back area RSSI : -73 dBm SNR : 14.3 dB
Technical Inform	nation		Confirm that me location matche Otherwise,modi	erchandise and confession for above.
Device Type:	Sensor		settings.	

## **Remerchandising Steps**

For the position to be in compliance with the site plan. You will need to update the site plan in the Web Portal prior to enrolling the devices. As a reminder, this site plan is intended to be uploaded at the regional level and a single site plan can be assigned to multiple store locations.

Navigate to the menu, select Configuration and then Site Plans.

									_
C Distantes	× +							- 0	×
< > C 0	https://insue-live-admin-preview.web.a	69				D R	e \star 🤅	6 6	
×	-							3	1
CASHIOARD CONFIGURATION MERCHANDISE	-								
BRANDS		Location		Merchandise					
SITES & STRUCTURE	-	bir Al		Rend Al	All	3			
DEVICE SETTINGS		Al	13	AL .	A1	10			
A USERS	To Jun 3, 2022	Poston All			UPG AB				
	PO FUTRS					RESET PLITERS			
	Display TV Manageme	et Display Security Do	wnloads						
	rations								



To update an existing site plan, select the download button and save the file on your local PC

	and and functions follows			0 0 A B	
	and apply in a start of the start			N N 10 10	-
A DE CELERA					
ite Plans					
Site plans define what sections and position s information is also used to report the status	s can be assigned to your InVue LIVE devices through the mobile App. of devices on the Dashboard.				
Import Det Templans File				Search	
Plat Name	Sile Type	Shert Oute	Datas		
IBC June 2 2022 Plan	Instrue Experience Center_Type	02-Aut-2022	ACTIVE	• •	
Infrae Test Center, Plan	Initue Text Center_Type	18-Jan-2022	AFTERS		
			naraj 25 -	- 10 K - C	
			inegraph 28 v	AND K A	
			marray 25 v	and R 🗧	
			ana in	944 K <	
			same 31	- 144 B. 4	
			anna Ba	<ul> <li>NN   &lt; &lt; 1</li> </ul>	
			anna Ba	- 440 R <	
				- 440 R <	
			3'	v van R €	





Adjust the Site Plan Name and Start Date for the date that the new plan will go into effect. This can be a date in the future if you decide to upload the site plan prior to a new planogram rollout.

×	AutoSave 🔘	on 🗄 r	IVE_Site_Plan_I	EC June 2 2022	Plan (1) 🝷					٩	Sea
Fi	le <u>Home</u>	nsert Page	Layout For	rmulas Data	Review	View	Add-ins	Help			
E.	Paste	X Cut I Copy → ≪ Format Paint	Calibri B I	- - -	12 ~ A^	Aĭ A v	= = <sub>=</sub> = = =	87	eb Wrap Text 師 Merge & C	enter ~	Gene
U	Jndo C	lipboard	r <u>s</u>	Font		r <u>s</u>		Alignn	nent	F3	
B3	~ :	$\times \checkmark f_x$	06-03-2022								
	А		В		с	D	Е	F	G	н	
1	Site Plan Name	E IEC June 3 2	022 Plan	•							
2	Site Type	InVue Exper	ience Cente	er_Type							
3	Start Date	06-03-2022		-							
4											
5											
6					3						
7					ď						
8											
9											

In the Positions tab, update the site plan to match the desired plan and save the file.

Æ	AutoSave 💽	Off 🛛 LIVE_Site_Plan_IEC June	2 2022 Plan (1) • Saved •	\$	O Search (Alt	:+Q)		
F	le Home I	nsert Page Layout Formulas	Data Review View	Add-ins Help				
6	Paste	X Cut Calibri Copy → B I U → Format Painter	<ul> <li>12 → A* A*</li> <li>12 → A* A*</li> <li>12 → Δ → Δ →</li> </ul>	E = = ≫ ~ (b Wrap Text E = = = = = = = = = = = = = = = = = = =	General \$ ~ %	9 €8 -	Conditio	nal Forma g ~ Table
_	Indo C	ipboard Is	Font 19	Alignment	a Num	ber	19	
E3	4 ~ :	$\times \checkmark f_x$ Security						
1	A	В	с	D		E	F	G
25	OSA Fixture	Bottom Shelf, Position 7	9201-204	Pepsi		OSA	342	
26	OSA Fixture	Bottom Shelf, Position 8	9201-203	Diet Pepsi		OSA	342	
27	OSA Fixture	Bottom Shelf, Position 9	9201-202	Pepsi Zero		OSA	342	
28	Mobile Table	Position 1	9201-1074	Galaxy A5		Security		
29	Mobile Table	Position 2	9201-1082	Samsung Galaxy Note 9		Security		
30	Mobile Table	Position 3	9201-1055	Huawei Mate Pro		Security		
31	Mobile Table	Position 7	9201-1080	iPhone SE		Security		
32	Mobile Table	Position 8	9201-1072	Samsung		Security		
33	Mohile Table	Position 9	9201-1070	Samsung		Security		
34	Mobile Table	Position 10	9201-1057	Apple iPhone 11		Security		
35	Mobile Table	Position 11	9201-1050	Samsung		Security		
36	Mobile Table	Position 12	9201-1066	Samsung		Security		
37	Mobile Carrier	Wireless Experience Showcase	9201-1037	Galaxy S8		Security		
38	TV Wall	TV Position 1	9201-1003			TV		
39	TV Wall	TV Position 2	9201-1013			TV		
40	TV Wall	TV Position 3	9201.1008			TV		

	Λ
U	-7

**1**3

To upload the new site plan, navigate back to the Web Portal and select Import.

3 Line Dapley X +					_	
C O https://www-live-admin-preview	web.app/tettings/plans		P	A* @ 10	0	4
ite Plans						
Site plans define what sections and position a information is also used to report the status	s can be assigned to your InVue LIVE devices through the mobile App. of devices on the Dashboard.					
Import Oct Template File				feasth		
Plan Name	Site Type	Start Date	Status			
IEC June 2 2022 Plan	trisue Experience Center_Type	02-Jun-2022	ACTIVE		• •	
Invive Test Center_Plan	Insue Test Center_Type	18-Jan-2022	ACTIVE		• •	٠
			6000 B -			
			Analisi ji s			
			and a second sec			
			6.0998 B			
			6.0998 B			
			una di			





(16)

You can navigate to your saved file or simply drag and drop the file into the window.



Finally Select Import and then Confirm.





To exchange the equipment on the stand, first disarm the sensor.







Remove the sensor from the stand and use the magnet key to remove the sensor cable from the sensor.





Remove the screws holding the sensor to the old merchandise.







Install the sensor on the new merchandise.





Place the sensor with the new merchandise on the stand.







To update the app, first navigate to the position on the LIVE Display app and select device settings.



23 Edit the device information to match the updated site plan by pressing the pencil icon next to the Merchandise Name.

2:21 🗅 😁 🕅 4		2 O I
< LIVE		
	Settings	
Туре:	OnePOD Securi	ty Sensor
Device ID:	00040010EE	
Merchandise: Samsung - Sa	msung Galaxy	1
Section:		
Mobile Table		1
Position:		
Position 10		1
Alarm Module N	ame:	
Alarm Node		1
Cancel		





Edit the SKU, UPC or Model number for the new merchandise and select Next.



Validate that the information displayed is correct and select Save.

	Settings	
Туре:	OnePOD Security	Sensor
Device ID:	00040010EE	
Merchandise:		
Apple - iPhone 1	1	1
Section:		
Mobile Table		1
Position:		
Position 10		1
Alarm Module Nan	ne:	
Alarm Node		1
0		





Ensure that the sensor is placed on the stand and press Confirm to clear the compliance issue message.





Once the enrollment process is complete, the shield icon will turn green.



Rev0 07/25/22

