

# Quick Start Guide Desk Lane 3000 Kiosk



## What's in the box?

1. Card Terminal
2. Terminal cable
3. Power supply unit
4. Window decal



## Function Keys



- Menu - Use this button to access the main functions menu on the terminal
- Cancel - Use this button to cancel and revert back to the previous screen
- Clear - Use this button to clear back or delete characters when keying in text/numbers
- Enter - Use this button to confirm selection on the terminal

## Getting started

Connect the Terminal cable to the Lane 3000 Kiosk terminal by connecting the HDMI end to the back of the terminal as shown.



Connect the Power supply to the Terminal cable, and connect to an active Ethernet port. \*Note the Ethernet extension block and additional cable can be used to extend the cable if required.



## Setting a static IP address on the terminal

When the terminal is configured, the Menu buttons are disabled on the device.

To access the admin menu please follow these steps.

1. After reboot press "F" key followed by "654123" and the "F" key again.
2. The terminal will request an administrator password which is 123456 and ENTER.

You are now in the Admin Menu. Using the Up/Down keys, select "ETH setting", and then press ENTER

Speed change appears on screen select Link speed 100Mb/s and press ENTER.

Protocol Change will then appear on screen, press the RED button (cancel)

You can now set the terminal to the desired IP address. Use the Yellow button to clear the existing IP address, and key in the new IP address you wish to use. Press ENTER button to save the changes.

The next screen will display the Subnet mask this should not be changed press ENTER.

The final screen displays the gateway IP address again this should not need to be changed. Press ENTER.

Terminal will request to save changes, press ENTER. Terminal will reboot and the new IP address will be set.

The Terminal is now set up with the specified IP address and ready for integration.

## Support

[BOIPA.co.uk/customer-support](https://BOIPA.co.uk/customer-support)

[support@BOIPA.com](mailto:support@BOIPA.com)

 **BOI UK**  
Payment Acceptance

A division of 

EVO Payments UK Ltd trading as BOI UK Payment Acceptance is registered in the UK under Companies House number 13527680. Further trading name of EVO Payments UK Ltd is BOIPA UK. EVO Payments UK Ltd is authorised and registered by the Financial Conduct Authority under the Payment Services Regulation 2017 (FRN 959332) for the provision of payment services and under the Consumer Credit Act (FRN 966552) for the undertaking of terminal rentals. EVO Payments UK Ltd trading as BOI UK Payment Acceptance is not a member of the Bank of Ireland Group. BOI UK Payment Acceptance has entered into a marketing alliance with the Bank of Ireland (UK) plc. BOI and the Tree of Life logo are trademarks of The Governor and Company of the Bank of Ireland and are being used under license by EVO Payments UK Ltd, trading as BOI UK Payment Acceptance.